

U01 NVIS Antenna by DJ5RE (3D printable Parts and PCBs by DL2MAN)

U01 is a linked EFHW, designed for NVIS Communication:

For 40/20/15/10m operation: **open 40/60m link** and **open 60/80m link**

For 60m operation: **close 40/60m link** and **open 60/80m link**

For 80/17m operation: **close 40/60m link** and **close 60/80m link**

Use Broadband-Transformer according to your needs

Cut wire lengths of sections (+ additional length for insulator/link loops)
Eg 40m segment: Cut 20,02m wire, use 19,77m between elevation point and transformer, use 15cm loop to feed from transformer and 10cm loop for link connection

For more details, PCB-Files and 3D-Print Files visit:
<https://dl2man.de/antennas>



